

NILES SERIES

NII -A





EXAMPLE
NIL-A-PSMH-150-208-BLK

NIL-A	_	_	_	_
Series	Ballast	Wattage	Voltage	Color

INSERTS	SOURCE	MEDIUM MOGUL	VOLTAGE	COLOR OF POWDER COAT FINISH	
FROSTED (CLEAR) WHITE (MILKY)	INC CFL HPS PSMH LED	0 50w 70w 100w 0 250w 150w 175w	120v MULIT TAP 120v 240v 208v 277v 277v PLEASE SPECIFY VOLTAGE	☐ (BLK) BLACK☐ (BRZ) BRONZE☐ (GRN) GREEN	☐ (HG) HAND BRUSHED GREEN☐ (HR) HAND BRUSHED GRAY☐ CUSTOM

LUMINAIRE SPECIFICATION

HOUSING

The post top shall be core cast aluminum. Aluminum shall be certified as pure #356 alloy, free of any porosity, foreign materials or cosmetic fillers. Castings shall be uniform wall thickness with no warping or mold shifting. Minimum wall thickness shall be 3/16°. Electrical components are mounted in the ballast canister. The ballast canister shall be mounted in the post top with three stainless steel screws. The optional refractor will be a borosilicate class refractor designed for either a type III or type V light distribution pattern.

LICHT WATTACE COCKET

ELECTRICAL

All electrical components and materials shall be UL-recognized and wired by a certified UL technician. All Niland ballasts are high power factor rated for -30°C/-20°F starting. Medium and Mogul base sockets are 4 KV rated. The electrical assembly is prewired with quick disconnects for servicing. Fixture shall be UL certified for wet locations

MOUNTING

Fixture shall be mounted to ∅3"O.D.x3"H. tenon with stainless steel allen head set screws (8 @ 90°)

RELAMPING

The lamp is accessed by loosening the $\frac{1}{4}$ -20X1" S.S. Button Head Socket Cap Screw mounted on the luminaire lid.

FINISH

Fixture finish shall consist of degreasing, phosphate acid etching with 140°+ deionized water, rinsed, oven dry off and top coated with a thermoset TGIC super polyester powder coat finish designed not to chalk or fade for many years. All Niland Company powders must pass a minimum 3000-hour salt spray test for corrosion resistance.

<u>CERTIFICATION</u>

The Fixture shall be UL-Listed for wet location use, and all HID listings.

WARRANTY

Fixture shall be warranted to be free of defects for five years. Ballast components shall carry the ballast manufacturers limited warranty of two years.

PHOTOMETRICS

Complete photometric data for all fixtures is available in IES-formatted 3.5 disks. A certified independent laboratory performs all testing. Call the Niland Company directly for more information.

 Catalog Name:NIL—A
 Date: 02.15.18

 Revision History:N/A
 Revision #: 0

 Niland Approval: Luis M.Gomez Customer Approval: Page: 3 of 3



Riland Company

NILAND COMPANY • PH: (915) 779-1405 • FAX: (915) 779-3618 • E-MAIL: INFO@NILANDCO.COM
320 N. Clark El Paso, Tx 79905 • PH: 800-648-9013 • FAX: 888-779-3065 • WEB PAGE: HTTP://www.nilandco.com